heatit

Z-WAVE

heatit CONTROLS

PRODUCT INFO Heatit Z-Push Wall Controller

FEATURES

- Wireless battery operated wall switch - Matte finish
- Designed for controlling lights, blinds, relays, dimmers etc.
- Fits System 55 frames
- SmartStart
- Controls up to 3 seperate groups and 5 devices per group
- 10 scene triggers per rocker
- Easy to install with screws or double-sided adhesive tape
- Firmware update (OTA)
- Supports encryption modes S0, S2 Authenticated Class, S2 Unauthenticated Class

This product is a security-enabled Z-Wave Plus product with encryption. The product must be used with a security-enabled Z-Wave Controller in order to fully utilize the product.

TECHNICAL DATA

Protocol	Z-Wave
Chip	Z-Wave 700 chip
Battery	1 x CR2450 battery
Battery life	Approx. 1 year with default settings and max 10 interactions per day.
Buttons	1, 2 or 3 rockers
Ambient temperature	5°C to 40°C (0°C to 40°C storage)
Humidity	Max 95% RH
Range RF	Min. 40 meters
IP Code	IP 20
Size (LxWxH)	55 x 55 x 14mm
Approvals	Z-Wave Plus V2, CE

MAINTENANCE


The device is maintenance-free, but must never be covered.
Indoor installation.

WARRANTY

2 years

ART. NO.	PRODUCT	COLOR	FREQUENCY
45 126 92	Heatit Z-Push Wall Controller	White RAL 9010	EU 868.4MHz
45 126 64	Heatit Z-Push Plastic Kit	White RAL 9010	

The product is also available in other Z-Wave frequency versions on request.



The Heatit Z-Push Wall Controller is supplied with all the three sets of rockers in the box.

HEATIT Z-PUSH WALL CONTROLLER

- Battery operated wall switch

NEW



RAL 9010
Matte finish

SMART START

S2 SECURITY


Z-WAVE PLUS

The Heatit Z-Push Wall Controller is a wireless wall mounted Z-Wave Controller. It has mounting options for 1, 2 or 3 rockers, allowing for easy and practical management of your Z-Wave products. The switch can be set up to control scenarios or work in association with other Z-Wave products. Each rocker switch has a dual color LED to indicate button actions.

The Wall Controller is coin cell battery powered.
The product is intended primarily for residential applications.

Heatit Z-Push Wall Controller has SmartStart. This feature allows the user to include all devices with SmartStart by scanning the QR codes on the devices. On startup all the devices will automatically be included in the gateway (requires SmartStart compability).

The product comes in a matte finish.
Fits System 55 frames.



Ver. 2022-B

heatit.com

All electrical installations must be carried out by a licensed electrician.
The product must be installed in accordance with our installers manual or national building codes.

2 yr WARRANTY

CE

WARRANTY - YOUR SAFETY

Heatit Controls AB can not be held liable for typographical errors, other errors or omittances in our information. Product specifications may change without further notice. Warranty does not apply to batteries.