


FDV

BA- Lighting AS

BA23-AL08-10-12W-S


Introduction






Detection Pattern

Ceiling Mounting pattern (Unit: m)



Wall Mounting pattern (Unit: m)



High detection area Low detection area

BA- Lighting surface mounted ceiling light adopts high lumen SMD LED, fire-rated PC diffuser with even light output. IP54 waterproof structural design, it is an ideal replacement for damp locations. driver in top branded component with triac dimmable function, 120°wide beam angle.

- Up to 70% energy saving compared to standard CFL
- Long lifetime of 40,000 hours
- 120° wide beam angle
- CCT: 3000K 4000K 5000K 5700K
- No UV/IR light
- Environment friendly, without Mercury or any other hazardous substances

Daylight & Microwave Sensor

Detection area:

◆ 140 degree wide detective beam angle with 5~7 meters distance.

Working pattern:

◆ With sufficient natural light, when illuminance is more than 10lux, the light does not switch on when presence detected.

◆ With insufficient natural light:

- When illuminance is less than 10lux, the light switches on automatically when presence detected.
- With presence detected, light will never switch off, even the nature light is sufficient.
- After presence left, any movement detected within time-delay (30 seconds), the light will continuously work for another hold time(30 seconds), then switch off automatically until next movement detected.
- Hold time: 30S

Microwave Sensor

Detection area:

◆ 140 degree wide detective beam angle with 5~7 meters distance.

Working pattern:

◆ In any given lighting condition, the light switches on automatically when presence detected.

◆ After presence left, light will continuously work within time-delay (30 seconds),then switch off automatically.

◆ After presence left, any movement detected within time-delay (30 seconds), the light will continuously work for another hold time (30 seconds), then switch off until next movement detected.

◆ Hold time: 30S

Application Areas

Applicable for corridor, basement, garage, warehouse, monitoring, and other places of energy-saving indoor and outdoor lighting.

Certificate

CE RoHS



Technical Specifications

Model	Voltage	Power	Power Factor	Lumen (±5%)	Beam angle	CCT	Lifespan	CRI	Dimmable	Dimension
BA-AL08-10-12W-S	AC230V	12W	≥0.9	996	120°	3000K	40000h	≥80	No	Ø250*48mm
BA-AL08-10-12W-S	AC230V	12W	≥0.9	1056	120°	4000K	40000h	≥80	No	Ø250*48mm
BA-AL08-10-12W-S	AC230V	12W	≥0.9	1068	120°	5000K	40000h	≥80	No	Ø250*48mm
BA-AL08-10-12W-S	AC230V	12W	≥0.9	1020	120°	5700K	40000h	≥80	No	Ø250*48mm


Driver data Sheet

Driver data	Sensor	Main Power
Input rated Voltage	AC230V	AC230V
Frequency	50Hz	50Hz
Input Voltage	AC200-240V	AC200-240V
Efficiency	—	≥88%
No load wattage	—	≤0.4W
Total load Wattage	2W±0.5W	12W±1W
Power Factor	—	≥0.9
Rated input current	≤0.02A	≤0.07A
Full load output Voltage	—	60-75V
Rated output current	—	150mA
Output current range	—	150mA±5%
Power tolerance	—	±5%
Current output tolerance	—	±5%
Hold time	30S	—
Detection distance	5-7m	—
Battery duration	—	
Charge Period	—	
Short circuit protection	—	PASS
Over voltage protection	—	PASS
Over temperature protection	—	PASS
Withstand voltage	—	AC3750V

Fixture Compatibility


Rated Wattage	Electrical Classification	Ingress Protection	Operating Temp	Operating Humidity	Storage Temp
12W	II	IP54	-20°C~45°C	0~90%	-20°C~65°C

Wiring Diagram:




Spectral Distribution


3000K




4000K



5000K




5700K




Photometric Diagram


3000K




4000K




5000K



5700K




Polar Diagram Comparison




AVERAGE BEAM ANGLE (50%): 115.5 DEG


UNIT: cd

- C0/180, 115.4 deg
- C30/210, 115.7 deg
- C60/240, 115.6 deg
- C90/270, 115.3 deg




Driver lifetime & LED light decay rate





Temperature

- The testing is operated at 25°C
- The lifetime of capacitor, minimum of 5,000 hours if operated at 105°C, will be doubled whenever the temperature drops 10°C
- The highest withstand temperature of IC, MOS could be 120°C
- The highest withstand temperature of LED junction temperature is 150°C







The driver lifespan is based on capacitor working temperature.

Installation


1.Take out ceiling light and accessory pack from box




2. Knock-in the plastic anchor into ceiling




3. Remove screw, take out bracket




4. Fix bracket with screw into the ceiling



5. Open junction box, wire"L""N" to terminal block and mount ceiling light into the right place




6. Switch on



Packaging Information

	SIZE(CM)	N.W/pc (KGS)	G.W.(KGS)	Q'TY(PCS)
Carton	61*53.5*28.5	0.56	16.8	20

	CTNS	Q'TY(PCS)	VOLUME(CBM)
20" standard container	297	5940	28
40" standard container	595	11900	56



www.ba-lighting.no post@ba-lighting.no Tlf: 37 16 04 00
Adr.: Hovedgata 10, 4900 TVEDESTRAND